

# ASI-5/ASI-3 PROFINET-Gateways in Stainless Steel

Bihl  
+ Wiedemann

**ASI-5 – Great data bandwidth, short cycle times**

**Compatible with all ASI generations**

**ASI-5 Master and ASI-3 Master in one device**

**OPC UA server**

**1 ASI master, PROFINET device**

**PROFINET IO**

- offers IRT-technology
- 1 integrated Switch

**integrated web server for simple diagnostics**



(figure similar)

**Recognition of duplicate ASI addresses**

**ASI Earth Fault Detector integrated**

**ASI Noise Detector integrated**

**Optional Control III, programming in C**



Figure	Fieldbus interface <sup>(1)</sup>	ASI-5/ASI-3	Number of ASI networks, number of ASI Master <sup>(2)</sup>	Integrated decoupling, ASI current measurement in the gateway <sup>(3)</sup>	Diagnostic and configuration interface <sup>(4)</sup>	Recognition of duplicate ASI addresses <sup>(5)</sup>	ASI fault detector <sup>(6)</sup>	Programming in C <sup>(7)</sup>	Article no.
	PROFINET, OPC UA	ASI-5 + ASI-3 compatible	1 ASI network, 1 ASI-5/ASI-3 master	yes, max. 8 A/ ASI network	Ethernet fieldbus + Ethernet diagnostic	yes	yes	optional	BWU3848

**(1) Fieldbus interface**

Communication interface between fieldbus and gateway: interfaces for standardized fieldbus systems in industrial automation.

**PROFINET ASI Gateway:** interface for a PROFINET fieldbus

**OPC UA server:** interface for the OPC UA communication.

**(2) Number of ASI networks, number of ASI Master**

"Double Master": 2 ASI networks, 2 ASI-5/ASI-3 Masters.

**(3) Integrated decoupling, ASI current measurement in the gateway**

"yes, max. 4 A/ASI network": Data decoupling integrated in the gateway. Cost-effective power for 2 ASI networks with 1 power supply (optionally supply of multiple Single Gateways by 1 power supply). Operation with short cable lengths with standard 24 V power supply possible.

**(4) Diagnostic and configuration interface**

"Ethernet fieldbus + Ethernet diagnostic":

Access to ASI Master and Safety Monitor with Bihl+Wiedemann software by using the Ethernet diagnostic interface or Ethernet fieldbus interface.

The latest version of the device description file of the gateway is available in the "Downloads" section of the respective device.

**(5) Recognition of duplicate ASI addresses**

Detects whether the same address has been assigned to two ASI nodes. Frequent error when using a handheld addressing device.

**(6) ASI fault detector**

Checks the ASI line for interference effects such as noise, external voltages, ...

**(7) Programming in C**

Using a C-program offers the possibility to run mini-PLC functions with a gateway.

# ASi-5/ASi-3 PROFINET-Gateways in Stainless Steel



<b>Article no.</b>	<b>BWU3848</b>
<b>Fieldbus Interface</b>	
Type	PROFINET; 2 x RJ-45, integrated 2-Port-Switch, IRT capability Conformance Class B integrated switch complies with Class C (IRT capability)
Baud rate	100 MBaud
OPC UA interface	OPC UA server + web server
Conformance Class	Class B integrated switch complies with Class C (IRT capability)
Function	PROFINET IO Device Media Redundancy Protocol (MRP) Shared Device
Card slot	Chip card (BW4055) for storage of configuration data
<b>Diagnostic Interface</b>	
Type	Ethernet; RJ-45 acc. IEEE 802.3
Baud rate	10/100 MBaud half-/full duplex
OPC UA interface	OPC UA server + web server
<b>ASi</b>	
ASi specification	ASi-5 + ASi-3
Cycle time	<b>Cycle time ASi-5 (constant):</b> 1,27 ms for 384 bits input data + 384 bits output data <b>Cycle time ASi-3 (variable):</b> 150 µs * (number of ASi-3 nodes + 2)
Operating current	ca. 250 mA
Current per ASi network	max. 8 A
ASi Power24V capability <sup>(1)</sup>	yes
<b>Display</b>	
LCD	menu, indication of ASi addresses, error messages in plain text
LED power (green)	power ON
LED PROFINET (green/red)	green: PROFINET communication active red: PROFINET communication not active
LED config error (red)	configuration error
LED U ASi (green)	ASi voltage o.k.
LED ASi active (green)	ASi normal operation active
LED prg enable (green)	automatic address programming enabled
LED prj mode (yellow)	in configuration mode
<b>UL-specifications (UL508)</b>	
External protection	An isolated source with a secondary open circuit voltage of $\leq 30 \text{ V}_{\text{DC}}$ with a 3 A maximum over current protection. Over current protection is not required when a Class 2 source is employed.
In general	UL mark does not provide UL certification for any functional safety rating or aspects of the above devices.

# ASi-5/ASi-3 PROFINET-Gateways in Stainless Steel



Article no.	BWU3848
<b>Environment</b>	
Applied standards	EN 60529 EN 61000-6-2 EN 61000-6-4
Operating altitude	max. 2000 m
Operating temperature	-25 °C ... +55 °C (no condensation permitted)
Storage temperature	-25 °C ... +85 °C
Housing	Stainless Steel, for DIN rail mounting
Pollution degree	2
Protection category	IP20
Tolerable loading referring to humidity	according to EN 61131-2
Maximum tolerable shock and vibration stress	according to EN 61131-2
Voltage of insulation	≥500 V
Weight	625 g
Dimensions (W / H / D in mm)	85 / 120 / 106

(1) ASi Power24V

The device can be operated directly on a 24 V (PELV) power supply. The gateway has been optimized with integrated data coupling coils and adjustable self-resetting fuses for safe use of powerful 24 V power supplies.

Article no.	BWU3848
Data decoupling integrated in the gateway	•
Current measurement of the ASi circuits	•
Self-resetting adjustable fuses	•
Cost-effective power for 2 ASi networks with 1 power supply	•

## Accessories:

- Chip card, memory capacity 512 kB (art. no. BW4055)
- Bihl+Wiedemann Suite - Software for Configuration, Diagnostics and Commissioning (art. no. BW2902)
- PROFINET Master Simulators Licenses (art. no. BW4754, BW4755)
- Power supplies, e.g.: 30 V power supply, 4 A, 1 phase (art. no. BW4218), 30 V power supply, 8 A, 1 phase (art. no. BW4219), 30 V power supply, 8 A, 3 phases (art. no. BW4220), 30 V Power Supply, 16 A, 1 phase (art. no. BW4221), 30 V Power Supply, 16 A, 3 phases (art. no. BW4222) (for further power supply units visit [www.bihl-wiedemann.de/en/products/accessories/power-supplies](http://www.bihl-wiedemann.de/en/products/accessories/power-supplies))