

24 Volt ASi-5/ASi-3 Gateways in Stainless Steel, 1 ASi-5/ASi-3 Master

Bihl
+ Wiedemann

ASi-5 – Great data bandwidth, short cycle times

Compatible with all ASi generations

ASi-5 master and ASi-3 master in one device

24 Volt ASi:

- The devices can be operated directly on a 24 V (PELV) power supply.
- With integrated data coupling coils and adjustable self-resetting fuses optimized for safe use also of powerful 24 V power supplies.

Available fieldbus interfaces:

- PROFINET IO: IRT-technology and 1 integrated Switch
- EtherNet/IP + Modbus/TCP in one device
- EtherCAT
- POWERLINK



(figure similar)

OPC UA server and integrated web server for simplified diagnostics

Recognition of duplicate ASi addresses

ASi Noise Detector integrated



| Figure | Type | Model | Fieldbus interface ⁽¹⁾ | Number of ASi networks, number of ASi Master ⁽²⁾ | Recognition of duplicate ASi addresses ⁽³⁾ | ASi fault detector ⁽⁴⁾ | Programming in C ⁽⁵⁾ | Article no. |
|--------|-----------------------------|---------|-----------------------------------|---|---|-----------------------------------|---------------------------------|-------------|
| | 24 Volt ASi-5/ASi-3 Gateway | Gateway | PROFINET, OPC UA | 1 ASi network, 1 ASi Master | yes | yes | no | BWU3847 |
| | 24 Volt ASi-5/ASi-3 Gateway | Gateway | EtherNet/IP + Modbus TCP, OPC UA | 1 ASi network, 1 ASi Master | yes | yes | no | BWU3849 |
| | 24 Volt ASi-5/ASi-3 Gateway | Gateway | EtherCAT, OPC UA | 1 ASi network, 1 ASi Master | yes | yes | no | BWU3854 |
| | 24 Volt ASi-5/ASi-3 Gateway | Gateway | POWERLINK, OPC UA | 1 ASi network, 1 ASi Master | yes | yes | no | BWU4016 |

⁽¹⁾ **Fieldbus interface**

Communication interface between fieldbus and gateway: interfaces for standardized fieldbus systems in industrial automation.

OPC UA server: interface for the OPC UA communication.

The latest version of the device description file of the gateway is available in the "Downloads" section of the respective device.

⁽²⁾ **Number of ASi networks, number of ASi Master**

"Single Master": 1 ASi network, 1 ASi Master.

⁽³⁾ **Recognition of duplicate ASi addresses**

Detects whether the same address has been assigned to two ASi slaves. Frequent error when using a handheld addressing device.

24 Volt ASi-5/ASi-3 Gateways in Stainless Steel, 1 ASi-5/ASi-3 Master

**Bihl
+ Wiedemann**

(4) **ASi fault detector**

Checks the ASi line for interference effects such as noise, external voltages, ...

(5) **Programming in C**

Using a C-program offers the possibility to run mini-PLC functions with a gateway.

| Article no. | BWU3847 | BWU3849 | BWU3854 | BWU4016 |
|----------------------------------|---|---|---|---|
| Interface | | | | |
| Fieldbus interface | PROFINET (RJ-45) | EtherNet/IP + Modbus TCP (RJ-45) | EtherCAT (RJ-45) | POWERLINK (RJ-45) |
| | <ul style="list-style-type: none"> • 2 x RJ-45, integrated 2-Port-Switch IRT capability • Conformance Class B • integrated switch complies with Class C (IRT capability) | <ul style="list-style-type: none"> • 2 x RJ-45, integrated 2-Port-Switch • Ethernet + Modbus TCP acc. to IEEE 802.3 | <ul style="list-style-type: none"> • 2 x RJ-45, integrated 2-Port-Switch • acc. to IEEE 802.3 | <ul style="list-style-type: none"> • 2 x RJ-45, integrated 2-Port-Switch • acc. to IEEE 802.3 |
| OPC UA interface | OPC UA server + web server | | | |
| Baud rates | 100 MBaud | 10/100 MBaud | 100 MBaud | 100 MBaud |
| Function | <ul style="list-style-type: none"> • PROFINET IO Device • Media Redundancy Protocol (MRP) • Shared Device | <ul style="list-style-type: none"> • Device Level Ring (DLR) (Ethernet/IP only) | – | – |
| Card slot | chip card (512 KB) for storage of configuration data | | | |
| ASi | | | | |
| ASi specification | ASi-3 + ASi-5 | | | |
| Cycle time | Cycle time ASi-3 (variable): 150 µs * (number of ASi-3 slaves + 2) Cycle time ASi-5 (constant): 1,27 ms for 384 bits input data + 384 bits output data | | | |
| Operating voltage | 24 V _{DC} (20 ... 31,6 V) (PELV voltage) | | | |
| Operating current | approx. 250 mA | | | |
| Current per ASi network | max. 4 A | | | |
| Length of ASi cable | with 24 V power supply: max. 50 m with 30 V power supply: max. 100 m with ASi-3 / max. 200 m with ASi-5 | | | |
| Display | | | | |
| LCD | menu, ASi indication of slave addresses, error messages in plain text | | | |
| LED power (green) | power ON | | | |
| Fieldbus | LED PROFINET | LED net | LED status | LED POWERLINK |
| | green: PROFINET communication active red: no PROFINET communication | green: EtherNet communication active | green: EtherCAT communication active | green: POWERLINK communication active |
| LED config error (red) | configuration error | | | |
| LED U ASi (green) | ASi voltage o.k. | | | |
| LED ASi active (green) | ASi normal operation active | | | |
| LED prg enable (green) | automatic address programming enabled | | | |
| LED prj mode (yellow) | in configuration mode | | | |
| UL-specifications (UL508) | | | | |
| External protection | An isolated source with a secondary open circuit voltage of ≤30 V _{DC} with a 3 A maximum over current protection. Over current protection is not required when a Class 2 source is employed. | | | |
| In general | UL mark does not provide UL certification for any functional safety rating or aspects of the above devices. | | | |

24 Volt ASi-5/ASi-3 Gateways in Stainless Steel, 1 ASi-5/ASi-3 Master



| Article no. | BWU3847 | BWU3849 | BWU3854 | BWU4016 |
|--|--|---------|---------------|---------|
| Environment | | | | |
| Applied standards | EN 61131-2 EN 60529 EN 61000-6-2 EN 61000-6-4 | | | |
| Operating altitude | max. 2000 m | | | |
| Operating temperature | 0 °C ... +55 °C | | | |
| Storage temperature | -25 °C ... +85 °C | | | |
| Housing | Stainless Steel, for DIN rail mounting | | | |
| Pollution degree | 2 | | | |
| Protection category | IP20 | | | |
| Tolerable loading referring to humidity | according to EN 61131-2 | | | |
| Maximum tolerable shock and vibration stress | according to EN 61131-2 | | | |
| Voltage of insulation | ≥500 V | | | |
| Weight | 500 g | | | |
| Dimensions (W / H / D in mm) | 85 / 120 / 83 | | 85 / 120 / 93 | |

| Article no. | BWU3847, BWU3849, BWU3854, BWU4016 |
|--|------------------------------------|
| Current measurement of the ASi circuits | - |
| Self-resetting fuses | • |
| Adjustable fuses | - |
| ASi earth fault monitor distinguishes between ASi cable and sensor cable | - |
| In version 1 gateway, 1 power supply for 2 ASi circuits: only 1 Gateway + 1 ASi power supply for 2 ASi networks | • |

Accessories:

- Chip card, memory capacity 512 kB (art. no. BW4055)
- Bihl+Wiedemann Suite - Software for Configuration, Diagnostics and Commissioning (art. no. BW2902)
- Power supplies, e.g.: 30 V power supply, 4 A, 3 phases (art. no. BW1927), 30 V power supply, 8 A, 3 phases (art. no. BW1676) (for further power supply units visit www.bihl-wiedemann.de/en/products/accessories/power-supplies)
- PROFINET Master Simulator (art. no. BW3035, BW3057)